# **UNDERWATER LED LIGHTS**

# SCM-10-CC

• 10 LEDs • 3,750 Lumens • 42W



#### **DESCRIPTION**

The SCM-10-CC Color Changing underwater light provides your vessel 42 watts of intense LED lighting with four intense colors in one light. SCM-10-CC's low profile design allows for many mounting locations. Easily switch between blue, white, green, and red. The unique stainless steel housing compliments the look of any trailer or lift kept boat.

## **FEATURES**

- Proprietary clear-gel-filled design, injected through entire unit — eliminates condensation and/or water intrusion under stress
- · Tough, polycarbonate lens
- Passivated stainless steel 316 material provides a durable corrosion resistant housing
- Transient surge and reverse polarity protection

   dramatically prolongs unit life
- Thermal throttling technology enables safe operation even out of water
- From simple on-off to full-feature lighting effects, unit is enabled for a host of control interfaces
- Select between 4 colors: blue, white, green and red or integrate control using Shadow-NET®

## **SPECIFICATIONS**

- Up to 3,750 lumens
- 120 degree beam angle
- 42 watts power draw
- 3.5 amps operating current draw @ 12 volts
- 10-30 volts input
- 10" (254 mm) x 2.4" (61mm) x 0.5" (13mm)
- IP68 fully submersible waterproof design
- 10 RGBW LEDs

#### **3 CONTROL OPTIONS**

# 1. Power Toggle Control

Quickly toggle power source to advance to next color or brightness level

## 2. Add Push Button Control

Shadow-Caster® offers the highest quality marine-grade push button controllers optimized to work seamlessly with your lighting requirement.

Part # SCM-SWITCH-O/O/MOMENTARY

#### 3. Add Shadow-NET® Control

Dramatic, full-feature control through your Multifunction Display (MFD) by adding the Shadow-NET® control module (SCM-MFD-LC) & app

## **INCLUDES**

- · Lighting unit
- 10' (6 m) submersible-grade cable
- 2 SS316 1" #8 PH screws
- · Standard 2 year warranty



## **Push Button Modes**

- · Any single color on
- Fade blue to white
- Fade through all 4 colors
- Strobe current color

